

VAMP 265

DIFFERENTIAL PROTECTION RELAY



- Suitable for generators, transformers and motors
- High stability against through faults
- 2nd harmonic blocking
- No CT ratio correction needed
- Selectable connection groups
- Disturbance recorder
- Various communication protocols including SPA Bus, Profibus, Modbus, Modbus TCP, IEC 61850, IEC 60870-5-101, IEC 60870-5-103, TCP/IP



Main technical data/ VAMP 265

Auxiliary voltage, U _{aux}	40...265 V ac / dc (optionally 18...36 Vdc)	
Rated phase current I _n	1A or 5A	
- current measuring range	0...50 x I _n	
Rated neutral current I _{0n}	1A or 5A	
- current measuring range	0...5 x I _n	
Thermal Withstand	4 x I _n (continuous), 100 x I _n (for 1 s)	
Rated frequency f _n	45...65 Hz	
- frequency measuring range	16...75 Hz	
Digital inputs (wetting voltage)	6 pcs	
- internal operating voltage	+48 V dc	
Trip / control contacts	2 pcs	
Alarm contacts	5 pcs	
Tests and environment		
Emission	EN 55022	
Immunity	IEC 60255-22-1, IEC 60255-11, EN 61000-4-6, EN 61000-4-5, EN6100-4-4, EN 61000-4-3, EN6100-4-2	
Insulation test	IEC 60255-5	
Surge voltage	IEC 60255-5	
Vibration shock	IEC 60255-21-1	
Operating temperature	-10...+55° C	
Relative humidity	<95 %, no condensation allowed	
Degree of protection (IEC 60529)	IP54, flush mounted	
Weight	4,2 kg	
Dimension (w x h x d)	209 x 155 x 225 mm	
Protection stages		
Overcurrent protection stages		
Differential overcurrent stages	ΔI >, ΔI >>	87
Overcurrent stages	I >, I' >, I >>, I' >>	50 / 51
Current unbalance stages	I ₂ >, I' ₂ >	46
Thermal overload protection	T >	49
Earth-fault protection stages		
Earth fault stages	I ₀ >, I ₀ >>, I ₀ >>>, I ₀ >>>>	50N / 51N
Programmable stage		
Programmable stage	Prg1...8	
Arc protection (option)		
Arc protection stages	ArcI >, ArcI' >	50ARC
Arc protection stages	ArcI ₀₁ >, ArcI ₀₂ >	50NARC
Other		
Disturbance recorder	All analogue channels and binary inputs / outputs	
Circuit breaker failure protection	CBFP	50BF
Trip circuit supervision	TCS	
Measurements		
Currents	IL1, IL2, IL3, L1 angle, L2 angle, L3 angle I'L1, I'L2, I'L3, L'1 angle, L'2 angle, L'3 angle	
Winding current	IL1w, IL2w, IL3w, I'L1w, I'L2w, I'L3w	
Differential currents	dL1, dL2, dL3, ΔL1φ, ΔL2φ, ΔL3φ	
Residual current	I ₀ (%)	
Current diagram (1		
- winding currents	IL1, IL2, IL3, I'L1, I'L2, I'L3	
- differential currents	ΔIL1, ΔIL2, ΔIL3	
Harmonics	IL1, IL2, IL3, I'L1, I'L2, I'L3	
Note: ¹⁾ with VAMPSET software		
Communication protocols		
IEC 61850		
IEC 60 870-5-101		
IEC 60 870-5-103		
Transparent TCP/IP		
Modbus TCP		
Modbus RTU		
Profibus DP		
SPA		

Vamp Ltd
P.O.Box 810
FI-65101 VAASA
Finland

Visiting address:
Vaasa Airport Park
Yrittäjänkatu 15
Vaasa, Finland

Tel: +358 20 753 3200
Fax: +358 20 753 3205
Email: vamp@vamp.fi
http:// www.vamp.fi



ISO 9001:2000
certified company



We reserve the rights to product alterations without prior notice.
Copyright © Vamp Ltd. All trademarks are the property of their respective holders.